

IN11343CW

INSTALLATION INSTRUCTIONS

Please read carefully and save these instructions, as you may need them at a later date.

CAUTION

WARNING: Risk of Fire. Consult a qualified electrician to ensure correct branch circuit conductor. Min 90°C supply conductors.

Turn off the main power at the circuit breaker before installing the fixture, in order to prevent possible shock.

GENERAL

All electrical connections must be in accordance with local and National Electrical Code (N.E.C.) standards. If you are unfamiliar with proper electrical wiring connections obtain the services of a qualified electrician.

Remove the fixture and the mounting package from the box and make sure that no parts are missing by referencing the illustrations on the installation instructions.

ASSEMBLY AND INSTALLATION

1. Put bottom ring (20) onto the bottom nipple end of lamp body (18) and secure with finial (21)
2. Put glass (19) onto bottom ring (20), then put top ring (17) onto glass (19) making sure the top nipple end of lamp body (18) extends through the center hole on top ring (17).
3. Thread hex nut(16) and loop (15) onto the nipple end of lamp body (18).
4. Adjust the chain (14) to your desired length, and connect loop (15) with lower chain lock (13) and chain (14).
5. Attach mounting bar (08) to outlet box (01) with box screws (09).
6. Pass the power supply cord and ground wire through chain (14), collar loop (12), canopy (11), nipple (10), and into outlet box (01).
7. Make wire connection with white wire (02) and black wire (03). Use wire connectors (05) to secure the connections. Secure ground wire (04) and ground wire from the fixture to mounting bar (08) with ground screw (07).
8. Screw nipple (10) into collar loop (12), then screw nipple(10) into mounting bar (08) and tighten with hex nut (06).
9. Use upper chain lock (13) to connect chain (14) to collar loop (12).
10. Raise canopy (11) to the ceiling, then secure in place by tightening threaded ring onto collar loop (12).
11. Hang the crystal ball (22) to the bottom of finial (21).

INSTALLATION IS NOW COMPLETE.

