


CRYSTORAMA LIGHTING



ASSEMBLY INSTRUCTION MODEL #MSL-316-SA




Crystal Sets

WARNING:



Electrical Danger



Turn Power Off

All electrical components must be installed by a licensed electrician in accordance with the National Electric Code and the appropriate local electrical codes.



You will need 6-Candelabra Base Bulb

40 Watts Recommended 60 Watts Max.

USE LED BULBS FOR EXTENDED USE

THIS FIXTURE IS DAMP RATED

How to install

1. Attach the mounting strap onto the outlet box.
2. Decide the preferred hanging height and choose the correct length of chain needed.
3. Raise the fixture up to the ceiling and do the wire connection. Secure the canopy over the outlet box with the two ball nuts.
4. Place the candle sleeve onto the socket, and insert recommended bulb(not included).
5. Screw the crystal flowers onto the metal frame.


How to replace the bulb

1. Identify the stem A that is removable.(There is a screw on the bottom of it)
2. Move it around to make the bulb easily accessible.



WARNING: This product can expose you to Lead, which is known to the State of California to cause cancer and/or birth defects or reproductive harm. For more information go to www.P65Warnings.ca.gov.

PART NUMBER MODEL #MSL-316-SA



Part Number

- A. (1) - Mounting Hardware
- B. (1) - Canopy(W4.7",H0.8") #XRE314SACAN4.7IN
- C. (1) - Decorative Metal Leaves
- D. (2)- Ball Nut #XRE306SABANU
- E. (2) - Loop
- F. (2) - Quick Link
- G. (1) -Hanging Chain(72",4mm) #XRE306SACHA4MM
- H. (1) - Fixture Loop
- I. (1) - Metal Cap
- J. (1) - Center Stem(14.37",9.3mm) #XRE316MTSTEM14.3IN
- K. (6) - Candle Sleeve(W.5", H1.97") #XRE31SACDL1.97IN
- L. (1) - Finial #XRE306SAFIN